



802.11a/b/g/n WLAN USB Adapter

802.11a/b/g/n USB 無線網卡，可外接高增益網路天線功能的無線 USB 網卡，安裝後就可以直接上網搜尋無線訊號穩定使用。台灣自產自銷，繁體中文介面操作。

在無線分享器(無線 AP)設定為 IEEE802.11a/b/g/n 無線環境下，輸出功率為 29dBm(800mW)，功率強可搭配高增益網路天線讓傳輸與接收的距離超遠，在無遮蔽阻礙環境下傳輸距離可達 1000 公尺的距離，接收已開放的無線訊號穩定不中斷。也可外接小天線及三角基座方便外出攜帶在戶外環境下使用，適合出差與遠行改善 Notebook 訊號弱的缺點。

外接小天線或連接同軸電纜線介面接頭為 RP SMA Female(與無線 AP 相同)，請使用 RP SMA Male 的連接接頭串接，直接接上小天線接收訊號，或串接同軸電纜線 + 高增益網路天線搭配使用，讓住家及辦公地方可穩定接收開放訊號使用。適用於大坪數的飯店/大賣場/辦公室/住家客廳房間。

高功率網卡晶片搭配高增益天線收訊使用效果更穩定



Specification :	
Standard:	IEEE 802.11a/b/g/n (WiFi Compatible)
Frequency Band:	5.1Ghz ~ 5.85GHz; 2.412GHz ~ 2.484GHz unlicensed ISM band
Data Rate:	IEEE 802.11a: Up to 54Mbps
Output power:	IEEE 802.11b: up to 11Mbps
	IEEE 802.11g: up to 54Mbps
	IEEE 802.11n: Up to 300 Mbps
	802.11a : 23±1.5dBm
Power Consumption:	802.11b/g : 28±1.5dBm
	802.11b/g/n : 28±1.5dBm
	Transmit: <500mA Receive: <300mA
Antenna	1x printed antenna on board
Security:	1x Dual Band Antenna (SMA connector)
	WEP (64/128/256bit), WPA, WPA-PSK,
I/O Interface:	WPA2 TKIP/AES, WPA2-PSK
	USB2.0
Operating System:	Windows98, SE, ME, 2000, CE, XP, SP2, Vista, 7, MAC, Linux
Operating Temperature:	-20°C ~ +70°C
Storage Temperature:	-40°C ~ +80°C
Humidity:	10 ~90% (non-condensing)
LED:	Link/Active